

VM/370 Format/Allocate

The FORMAT/ALLOCATE program is a stand-alone application which prepares portions of volumes to be used by the VM/370 control program. Because it is such an important part of system setup and maintenance, we will use an example session to describe its use.

Using Format/Allocate

Logged in as userid **MAINT**, locate the FMT program. All stand-alone utilities are, by convention, consistently given the filename IPL <utilityname> * and are usually located on the 190(S) disk.

Locating FMT

General User

```
I ipl * * IPL DDR B2 IPL DIR B2 IPL FMT B2 IPL DDR S2 IPL DIR S2 IPL FMT S2 IPL IBCDASDI S2 Ready;  
T=0.01/0.01 21:14:53
```

The file we are searching for is IPL FMT S2. The one on MAINT's B-disk is just a copy of the one on the 190(S) disk.

Starting FMT

1. Spool the virtual punch unit to our own virtual reader:

```
spool pun *  
Ready; T=0.01/0.01 20:59:21
```

2. Punch the file (with NO punch headers) to our virtual reader:

```
punch ipl fmt s2 (noheader  
PUN FILE 0501 TO MAINT COPY 01 NOHOLD  
Ready; T=0.01/0.02 21:00:41
```

3. Move the file we just deposited in the virtual reader, to the front of the reader's queue:

```
order rdr 0501  
0001 FILE ORDERED  
Ready; T=0.01/0.01 21:00:46
```

4. Now IPL from the virtual reader (defined by convention as Device 00C):

```
ipl 00c  
VM/370 FORMAT/ALLOCATE PROGRAM RELEASE 6  
ENTER FORMAT OR ALLOCATE:
```

The utility is now ready!

Verify Our Work

As a follow-up task in this system, we discovered that VOLSER VM50-6 has no valid allocation byte map and one needs to be instantiated. Because we have user MDISKS defined on this volume - we are only going to perform our task on a portion of the volume: Cylinder 0.

Verify our virtual DASD Configuration by issuing the command `#cp q v dasd:`

```
CP Q V DASD
DASD 093 3350 VM50-4 R/W 0040 CYL
DASD 094 3350 VM50-4 R/W 0040 CYL
DASD 141 3350 VM50-1 R/W 0555 CYL
DASD 190 3350 VM50-1 R/W 0061 CYL
DASD 191 3350 VM50-1 R/W 0035 CYL
DASD 193 3350 VM50-1 R/W 0035 CYL
DASD 194 3350 VM50-1 R/W 0035 CYL
DASD 19D 3350 VM50-2 R/W 0070 CYL
DASD 19E 3350 VM50-2 R/W 0070 CYL
DASD 232 3350 VM50-2 R/W 0555 CYL
DASD 233 3350 VM50-3 R/W 0555 CYL
DASD 234 3350 VM50-4 R/W 0555 CYL
DASD 235 3350 VM50-5 R/W 0555 CYL
DASD 236 3350 VM50-6 R/W 0555 CYL  <-- NOTE: This is the Device we seek.
DASD 294 3350 VM50-1 R/W 0035 CYL
DASD 299 3350 VM50-1 R/W 0014 CYL
DASD 393 3350 VM50-1 R/W 0085 CYL
DASD 394 3350 VM50-1 R/W 0110 CYL
DASD 494 3350 VM50-1 R/W 0017 CYL
```

Noting the Full-Pack MDISK for VOLSER VM50-6 on Device 236 of Type 3350, we can then proceed with our tasks.

We first VERIFY that this is the volume that we seek by performing a “no-write” allocate action. (The lower-case text shows commands we type, UPPER-CASE text shows the responses from the utility.)

- Verify a volume we already know to be properly allocated: vm50-1 (the VM system residence volume):

```
ENTER FORMAT OR ALLOCATE:
allocate
ALLOCATE FUNCTION SELECTED
ENTER DEVICE ADDRESS (CUU):
141
ENTER DEVICE TYPE:
3350
ENTER DEVICE LABEL:
vm50-1
ENTER ALLOCATION DATA FOR VOLUME VM50-1
TYPE CYL  CYL
```

```
end
ALLOCATION RESULTS
PERM 0000 0010
DRCT 0011 0012
PERM 0013 0019
TEMP 0020 0079
TDSK 0080 0099
PERM 0100 0554
DEVICE 141 VOLUME VM50-1 ALLOCATION ENDED
```

Success! The volume validates against the output of the analysis tool:

* Device Address 141

```
Volume      : E:\Emulation\Vm370.6Pack.1.3.Orig\disks\vm3350-1.141.cckd
Shadow      : sf=E:\Emulation\Vm370.6Pack.1.3.Orig\disks\shadows\vm3350-1_
Composed On : C:\Users\sjzop\AppData\Local\Temp\vm3350-1.141.cckd.CV.cckd
```

VolSer(VM50-1) :555 cylinders

Allocations Found On This Volume

```
ALLOCATE StartCyl EndCyl
```

PERM	0000	0010
DRCT	0011	0011
DRCT	0012	0012
PERM	0013	0019
TEMP	0020	0079
TDSK	0080	0099
PERM	0100	0554

Now we validate our candidate device 236 VOLSER vm50-6

ENTER FORMAT OR ALLOCATE:

allocate

ALLOCATE FUNCTION SELECTED

ENTER DEVICE ADDRESS (CUU):

236

ENTER DEVICE TYPE:

3350

ENTER DEVICE LABEL:

vm50-6

```
DMKFMT736E IO ERROR 236 CCHHR = 0000000004
```

SENSE=00080000800

```
DMKFMT735E FATAL DASD I/O ERROR CSW=00002C680E000000
```

The format program receives an I/O Error from the VM/370 Control Program indicating a failure to read CYLINDER 000 HEAD 00 RECORD 4 (the location of the allocation byte map). This is the correct volume.

Execute FORMAT/ALLOCATE

We only need to format CYLINDER 000 to perform the allocation. This is done in two easy steps.

1. Perform the FORMAT operation:

```
ENTER FORMAT OR ALLOCATE:
format
FORMAT FUNCTION SELECTED
ENTER DEVICE ADDRESS (CUU):
236
ENTER DEVICE TYPE:
3350
ENTER START CYLINDER (XXX OR XXXX) OR "LABEL":
000
ENTER END CYLINDER (XXX OR XXXX):
000
ENTER DEVICE LABEL:
vm50-6
FORMAT STARTED
FORMAT DONE
0000 NO. PAGE RECORDS WITH READ-CHECK ERRORS
```

2. Perform the ALLOCATE operation:

```
ENTER FORMAT OR ALLOCATE:
allocate
ALLOCATE FUNCTION SELECTED
ENTER DEVICE ADDRESS (CUU):
236
ENTER DEVICE TYPE:
3350
ENTER DEVICE LABEL:
vm50-6
ENTER ALLOCATION DATA FOR VOLUME VM50-6
TYPE CYL  CYL
perm 000 554
end
ALLOCATION RESULTS
PERM 0000 0554
DEVICE 236 VOLUME VM50-6 ALLOCATION ENDED
```

3. Verify both operations:

```
ENTER FORMAT OR ALLOCATE:
allocate
```

```
ALLOCATE FUNCTION SELECTED
ENTER DEVICE ADDRESS (CUU):
236
ENTER DEVICE TYPE:
3350
ENTER DEVICE LABEL:
vm50-6
ENTER ALLOCATION DATA FOR VOLUME VM50-6
TYPE CYL  CYL
end
ALLOCATION RESULTS
PERM 0000 0554
DEVICE 236 VOLUME VM50-6 ALLOCATION ENDED
ENTER FORMAT OR ALLOCATE:
```

Restart CMS

We are done - so we can just return to CMS by entering the `#cp ipl cms` command:

```
CP IPL CMS
CMS VERSION 6.0 - 03/11/18 19:50
```

```
Y (19E) R/0
U (19D) R/0
B (094) R/0
D (194) R/0
E (294) R/0
F (394) R/0
```

```
+-----+
--+
|           Welcome to VM/370 and VM/380 "SixPack" version 1.3!
|
+-----+
--+
```

For a list of CMS commands, type `HELP CMSCMDS`. For a list of CP commands, type `HELP CPCMDS`.

Other useful documentation and sample programs can be found on MAINT 19D, accessed as your U disk.

For more details, type `HELP WELCOME (MORE`

For information on building the CP or CMS nucleus, read `SYSPROG MEM0`.
Ready; T=0.01/0.05 21:08:28

That's it!

Now Shutdown VM, and let's re-run our analysis to obtain an
up-to-date analysis

.

The analysis looks good ...

Let's move on to [Enhancing the Operational Environment](#).

From:
<https://codex.sjzoppi.com/> - **Wizard of Odd**

Permanent link:
https://codex.sjzoppi.com/ibm360-370:use_the_format_allocate_program

Last update: **2020/12/27 21:05**

